Smart Cake/Kup/Lotis 115 Adj LED DE

127710XX 127711XX 127712XX 127713XX 127714XX 127715XX 127716XX 127716XX 127716XX 127716XX 127810XX 127810XX 127812XX 127816XX 127816XX 127816XX 127816XX 127816XX 127915XX 127

SMART CAKE ADJ 115 2 1 3 D +) driver Ø108 driver (🔶) driver driver SMART KUP ADJ 115 ELECTRICAL SPECS LED-FIXTURE Forward Voltage **Drive Current** Power (mA) (W) min (Vf) max (Vf) 350 16.5 19,2 6.2 INSTALL UNINSTALL 500 17,1 19,8 9,2 700 17,7 20,8 13,4 🚹 RED BLACK For serial connection, respect polarity! Not suited for connection to mains voltage. Combine with a Modular LED-driver. SMART LOTIS ADJ 115 LIGHT SOURCE - DO NOT TOUCH LED Touching the LED can result in permanent damage of the SERIAL CONNECTION: light source. The light source contained in this luminaire Ø150 mm shall only be replaced by the manufacturer or his service agent or a similar qualified person. DRIVER PREVENTING ELECTROSTATIC DAMAGE A discharge of static electricity may damage sensitive 100 mm components. Therefore do not touch the LED nor the stripped parts of the wires with bare hands. Always be ESD properly insulated by using ESD gloves. DRIVERS & ACCESSORIES

> Always use a serial connection for multiple luminaires on a single driver! Only use luminaires with the same input ratings!

For latest version of driver matrix and available accessories check www.supermodular.com or connect with your sales contact.



