

Dimmer compatibility guide

LED AR111 lamps 70008066-70008067



70008066



70008067

	PER 1	PER 5		PER 1	PER 5
BERKER 8542 12	-	100-10%		-	100-10%
+ RESISTOR YOKIS CHR3W	-	100-10%		-	100-10%
BERKER 2861 10	100-80%	100-10%		100-80%	100-10%
+ RESISTOR YOKIS CHR3W	100-80%	100-10%		100-80%	100-10%
JUNG 1224 LED UDE	100-50%	100-0%		100-50%	100-0%
+ RESISTOR YOKIS CHR3W	100-50%	100-0%		100-50%	100-0%
JUNG 225 NVDE	100-0%	100-0%		100-0%	100-0%
+ RESISTOR YOKIS CHR3W	100-0%	100-0%		100-0%	100-0%
BUSCH-JAEGER 6523 U-102	100-20%	100-0%		100-20%	100-0%
+ RESISTOR YOKIS CHR3W	100-10%	100-0%		100-10%	100-0%
GIRA 2385 00	100-20%	100-0%		100-20%	100-0%
+ RESISTOR YOKIS CHR3W	100-20%	100-0%		100-20%	100-0%
VADSBO VD100	100-30%	100-0%		100-30%	100-0%
+ RESISTOR YOKIS CHR3W	100-30%	100-0%		100-30%	100-0%
VADSBO VD200	-	-		-	-
+ RESISTOR YOKIS CHR3W	-	-		-	-
VADSBO VD300	100-0%	100-0%		100-0%	100-0%
+ RESISTOR YOKIS CHR3W	100-0%	100-0%		100-0%	100-0%
VADSBO VD600	100-0%	100-0%		100-0%	100-0%
+ RESISTOR YOKIS CHR3W	100-0%	100-0%		100-0%	100-0%
VADSBO LD200KRON	100-30%	100-0%		100-30%	100-0%
+ RESISTOR YOKIS CHR3W	100-30%	100-0%		100-30%	100-0%
NIKO 330-00700	100-0%	100-0%		100-0%	100-0%
NIKO 310-01900	100-0%	100-0%		100-0%	100-0%
NIKO 310-02800	100-0%	100-0%		100-0%	100-0%
NIKO 310-02900	100-0%	100-0%		100-0%	100-0%
EL TAKO EU12NPN-UC	100-10%	100-10%		100-10%	100-10%
TRUMP DIMMAX 420SL	100-10%	100-10%		100-10%	100-10%